
Operation





How to Calibrate?

mode wheel:

- Switch on press
- Show menu press
- Select function scroll
- Activate function press

esc button:

 Change between menu and measurement mode

std button:

• Short-cut to measure standard

Operate button:

• Switch on, select and measure

ect and measure



AE c DIN mod

AE p DIN mod

ESC ⇒ Data view

Solid

Light Silver

How to measure Differences?

- Select a stored standard, use "AUTO standard" or measure a standard
 Input standard name:
 - Change character ==> turn scroll wheel Move to next digit ==> press scroll wheel Move one digit back ==> press esc
- Input number of readings

•	Place	instrument	on	stand	arc

- Press operate to take a reading
- Copy predefined settings for data display
- Continue with sample readings

Note: All color data inclusive spectral data are saved and transferred to software.

1	Black/white	calibration
		C 111

- Select Setup Calibrate Black/White Calibration
- Place unit on black trap and confirm OK
- Place unit on white standard and confirm OK

Black/white calibration is requested every 3 months.

Color test

After a black and white calibration the instrument must be checked on the color reference included in the delivery content.

• Place unit on color reference and confirm OK

The color test is requested every 30 days. Make sure to perform it in laboratory environment (Temperature 20 - 25°C, Humidity 30 - 60%).

	AL"	∆a*	Δb°	ΔE*
-15°	0.05	0.13	0.01	0.14
15°	-0.45	0.08	0.00	0.45
25°	-1.00	0.02	-0.01	1.00
45°	-1.27	-0.00	0.22	1.29
75°	-0.20	0.16	0.45	0.52
110°	0.70	0.25	0.38	0.83
STAND	ARD 01		Differen	ncex

• First page displays color differences

SAMPL	E 001		D65/10°	2/2
	ΔS	∆s_i	∆S_a	
15°	4.93	-15.67	-8.89	
45°	1.48	-4.78	-0.30	
75°	1.75	-4.03	-4.07	
		ΔG	-0.52	
TAND	ARD 02		Differen	e

- Scroll to second page for sparkle and graininess results*
- * Only available with BYK-mac i

BYK-Gardner GmbH · Lausitzer Strasse 8 · 82538 Geretsried · Germany · Tel. +49-8171-3493-0 · Fax +49-8171-3493-140 · www.byk.com/instruments

Measure	•
-Continue last series	•
Absolute	•
Difference	•
Delete	•
Data view	•
Setup *	•

- How to measure Absolute Data?
 - Select Measure Absolute
 - Place instrument on sample
 - Press operate to take a reading
 - Default settings: average of 3
 - Input sample name: Change character ==> turn scroll wheel Move to next digit ==> press scroll wheel Move one digit back ==> press esc

How to use an Organizer?

Measure └Model 1 └Light Silver	-
Line 1	
Line 2	,
Delete	,
Data view	,
Setup *	,
STANDARD 02	Difference
	-Model 1 -Light Silver -Line 1 -Line 2 Delete Data view

Hood			D65/1	0° 3/3
	ΔL p	∆a p	∆b p	ΔEpD
-15°	0.05	0.11	-0.03	0.12
15°	0.05	0.08	-0.06	0.11
25°	-0.14	0.05	-0.11	0.19
45°	-0.22	0.02	0.13	0.26
75°	-0.13	0.15	0.32	0.38
110°	0.12	0.18	0.34	0.40
			ΔEt	0.27
Light Silver			Mo	del 1

- An organizer is a predefined sampling procedure that needs to be downloaded from the software smart-chart.
- Select style (Par1), color (Par2), paint line (Par3)
- Press operate to measure the first measurement zone
- After a measurement zone has been completed, press operate to move to the next zone
- To skip a measurement zone, press the mode wheel and select "Interrupt Statistic". The number of readings is set to zero.
- **Note:** "Interrupt" must be activated in the organizer!

How to change Settings?

Instrument settings and measurement parameters for each individual standard can be changed in Setup.

Overview Setup

Measurement Parameters	
Statistic	Define number of readings or select SMC mode
Color	Select angles, color scale, illuminant/observer for display
Effect*	Select effect scales
Fluorescence Limit	Define acceptable max. difference between fluorescent compensated and non-compensated reading as percen- tage of used color tolerance.
Sample Temperature Alarm	Set minimum and maximum temperature to alert alarm
Instrument	
Sample Curvature	Select pin sensitivity according to sample curvature
Automatic Measurement	Execute readings by pins on/off
Beeper	Turn beeper on/off
Language	Select language
Info	Info on Version, Calibration Dates, Free Memory
Date/Time	Set date and time
Display Time	Define time instrument is on
Display Brightness	Adjust display brightness.
Advanced	Activate/deactivate Interrupt Statistic, Input Parameter 2, Input Comment, Input ID, Input Checkzone

* Only available with BYK-mac i

BYK-Gardner USA · 9104 Guilford Road · Columbia · MD 21046 · USA · Phone +1-301-483-6500 · Fax +1-301-483-6555 · www.byk.com/instruments

